

## Annotations

- 1. The picture shows that the adjusting axle is on the H point;
- 2. The thermostat's capillary tube and the temperature sensing bulb are easy to damage, They couldn'd be damaged\pressed to flat/broke off, or it will influence the thermostat's function and temperature;
- 3. Thermastat's working temperature is 25°C, the capillary tub must be immersed in heat water of 30~80mm deep, or the testing result will not be correct;
- 4. Testing condition: the model of temperature variety is ≤1°C/1min.

- 1.H point temperature/OFF:85±4°C DIFF:5±3°C
- 2. The fixing electric voltage: AC250V The fixing electric current: 16A
- 3.Electrical strength: 2000VAC/1min/0.5mA
- 4. The touching electric resistance: <50m $\Omega$
- 5. Insulating electric resistance: >100M Ω
- 6. The highest temperature the main body can endured: 125°C
- 7. The hignest temperature the temperature feeling tube can endured: 120° C
- 8.Product's life:>100.000 times

