

Annotations

- $1. \ \mbox{The picture shows that the adjusting axle is on the H point;}$
- 2. The thermostat's capillary tube and the temperature sensing bulb are easy to damage, They couldn'd be damaged\pressed to flat/broke off, or it will influence the thermostat's function and temperature;
- 3. Thermastat's working temperature is 25°C, the capillary tub must be immersed in heat water of 30 \sim 80mm deep, or the testing result will not be correct;
- 4. Testing condition: the model of temperature variety is ≤ 1 °C/lmin.

- 1.H point temperature/DFF: $400\pm20^{\circ}$ C DIFF: $8\pm5^{\circ}$ C
- 2.The fixing electric voltageAC250V The fixing electric current16A
- 3.Electrical strength: 2000VAC/1min/0.5mA
- 4. The touching electric resistance <50 m Ω
- 5. Insulating electric resistance >100 M Ω
- 6. The highest temperature the main body can endured: 125 ${\tt C}$
- 7.The hignest temperature the temperature feeling tube can endured:350°C
- 8.Product's life:>10万次

